

TYPE NUMBER	MFR	APP	CMP	GBP MIN	SLEW RATE MIN	V <sub>s+</sub> MAX	V <sub>s-</sub> MAX	T <sub>OP</sub> MAX	A <sub>VOL</sub> MIN	V <sub>IO</sub> MAX	I <sub>B</sub> MAX	I <sub>IO</sub> MAX	PROT MAX	I <sub>OUT</sub> MIN	V <sub>OUT</sub> MIN	V <sub>ICM</sub> MAX	V <sub>IDP</sub> MAX	dV <sub>IO</sub> /dT MAX	P <sub>O</sub> MAX	I <sub>O</sub> MAX	CM RR MIN	PS RR MIN	R <sub>IN</sub> MIN	
SE532T	SJU	DGK	INT	.3MHZ		+15V	-15V	125C	88dB	6MV	300NA	100NA			14V	14V	16V	20uV/C		2MA	60dB	80dB		
SE535N(8)	MUG	HSR	INT	.3MHZ	5V/uS	+22V	-22V	125C	88dB	3MV	100NA	20NA	500MWF	5MA	12V	13V	30V	1.5uV/C		3MA	80dB	100dB		
SE535T	MUG	HSR	INT	.3MHZ	5V/uS	+22V	-22V	125C	88dB	3MV	100NA	20NA	500MWF	5MA	12V	13V	30V	1.5uV/C		3MA	80dB	100dB		
SE535V	MUG	HSR	INT	.3MHZ	5V/uS	+22V	-22V	125C	88dB	3MV	100NA	20NA	500MWF	5MA	12V	13V	30V	1.5uV/C		3MA	80dB	100dB		
SE540L	SJU	HCO	EXT		100V/uS	+27V	-27V	125C		7MV	3uA	0.7uA	1WF	12A						20MA	90dB	80dB	10K	
SE592A	SJU	BDO	EXT	20MHZ		+8V	-8V	125C	50dB	5MV	20uA	3uA	670MWF	2MA	1.5V	6V	5V			24MA	60dB	50dB	2K	
SE592F	MUG	BDO	EXT	20MHZ		+8V	-8V	125C	50dB	5MV	20uA	3uA	670MWF	2MA	1.5V	6V	5V			24MA	60dB	50dB	2K	
SE592K	SJU	BDO	EXT	20MHZ		+8V	-8V	125C	50dB	5MV	20uA	3uA	500MWF	2MA	1.5V	6V	5V			24MA	60dB	50dB	2K	
SE592N(14)	MUG	BDO	EXT	20MHZ		+8V	-8V	125C	50dB	5MV	20uA	3uA	670MWF	2MA	1.5V	6V	5V			24MA	60dB	50dB	2K	
SF.C2101A	THF	GPU	EXT			+22V	-22V	125C	94dB	2MV	75NA	10NA	500MWF	5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M	
SF.C2101APM	THF	GPU	EXT			+22V	-22V	125C	94dB	2MV	75NA	10NA	500MWF	5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M	
SF.C2107M	THF	GPK	INT			+22V	-22V	125C	94dB	2MV	75NA	10NA	500MWF	2MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M	
SF.C2107PM	THF	GPK	INT			+22V	-22V	125C	94dB	2MV	75NA	10NA	500MWF	2MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M	
SF.C2108A	THF	SBA	EXT			+20V	-20V	125C	98dB	0.5MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	5uV/C		6MA	96dB	96dB	30M	
SF.C2108M	THF	SBA	EXT			+20V	-20V	125C	96dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		6MA	85dB	80dB	30M	
SF.C2108PM	THF	SBA	EXT			+20V	-20V	125C	96dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		6MA	85dB	80dB	30M	
SF.C2110M	THF	VFA	INT		15V/uS	+18V	-18V	125C	0dB	4MV	3NA		500MWF	1MA	10V	15V	15V	50uV/C		6MA		70dB	10G	
SF.C2111M	THF	CPR	EXT			+18V	-18V	125C	100dB	3MV	100NA	10NA	500MWF			15V	30V			6MA				
SF.C2118M	THF	XSR	INT		50V/uS	+20V	-20V	125C	94dB	4MV	250NA	50NA	500MWF	6MA	12V	15V	1V			8MA	80dB	70dB	1M	
SF.C2201A	THG	GPU	EXT			+22V	-22V	85C	94dB	2MV	75NA	10NA	500MWF	5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	500K	
SF.C2201APT	THG	GPU	EXT			+22V	-22V	85C	94dB	2MV	75NA	10NA	500MWF	5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	500K	
SF.C2207	THF	GPK	INT			+22V	-22V	85C	94dB	2MV	75NA	10NA	500MWF	5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M	
SF.C2207PT	THF	GPK	INT			+22V	-22V	85C	94dB	2MV	75NA	10NA	500MWF	5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M	
SF.C2208	THF	SBA	EXT			+20V	-20V	85C	96dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		6MA	85dB	80dB	30M	
SF.C2208A	THF	SBA	EXT			+20V	-20V	85C	98dB	0.5MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	5uV/C		6MA	96dB	96dB	30M	
SF.C2208PT	THF	SBA	EXT			+20V	-20V	85C	96dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		6MA	85dB	80dB	30M	
SF.C2210	THF	VFA	INT		15V/uS	+18V	-18V	85C	0dB	4MV	3NA		500MWF	1MA	10V	15V	15V	50uV/C		6MA		70dB	10G	
SF.C2211	THF	CPR	EXT			+18V	-18V	85C	100dB	3MV	100NA	10NA	500MWF			15V	30V			6MA				
SF.C2218	THF	XSR	INT		50V/uS	+20V	-20V	85C	94dB	4MV	250NA	50NA	500MWF	6MA	12V	15V	1V			8MA	80dB	70dB	1M	
SF.C2301A	THF	GPU	EXT			+18V	-18V	70C	88dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	500K	
SF.C2301ADC	THG	GPU	EXT			+18V	-18V	70C	88dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	500K	
SF.C2307	THF	GPK	INT			+18V	-18V	70C	84dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C			70dB	70dB	0.5M	
SF.C2307DC	THF	GPK	INT			+18V	-18V	70C	84dB	7.5MV	250NA	50NA	500MWF	5MA	12V	15V	30V	30uV/C			70dB	70dB	0.5M	
SF.C2308	THF	SBA	EXT			+18V	-18V	70C	88dB	7.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	30uV/C		6MA	80dB	80dB	10M	
SF.C2308A	THF	SBA	EXT			+18V	-18V	70C	98dB	0.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	5uV/C		6MA	96dB	96dB	10M	
SF.C2308DC	THF	SBA	EXT			+18V	-18V	70C	88dB	7.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	30uV/C		6MA	80dB	80dB	10M	
SFC2310	THF	VFA	INT		15V/uS	+18V	-18V	70C	0dB	7.5MV	7NA		500MWF	1MA	10V	15V	15V	50uV/C		6MA		70dB	10G	
SF.C2310DC	THF	VFA	INT		15V/uS	+18V	-18V	70C	0dB	7.5MV	7NA		500MWF	1MA	10V	15V	15V	50uV/C		6MA		70dB	10G	
SF.C2310EC	THF	VFA	INT		15V/uS	+18V	-18V	70C	0dB	7.5MV	7NA		500MWF	1MA	10V	15V	15V	50uV/C		6MA		70dB	10G	
SF.C2311	THF	CPR	EXT			+18V	-18V	70C	100dB	7.5MV	250NA	50NA	500MWF			15V	30V			8MA				
SF.C2311DC	THF	CPR	EXT			+18V	-18V	70C	100dB	7.5MV	250NA	50NA	500MWF			15V	30V			8MA				
SF.C2311EC	THF	CPR	EXT			+18V	-18V	70C	100dB	7.5MV	250NA	50NA	500MWF			15V	30V			8MA				
SF.C2315DC	THF	GPU	EXT		3V/uS	+15V	-15V	70C	75dB	20MV	50NA	25NA		25MA	14V	13V	13V	50uV/C		3MA	60dB	74dB	1M	
SF.C2318	THG	XSR	INT		50V/uS	+20V	-20V	70C	88dB	10MV	500NA	200NA	500MWF	6MA	12V	15V	1V			8MA	70dB	65dB	500K	
SF.2318EC	THF	XSR	INT		50V/uS	+20V	-20V	70C	88dB	10MV	500NA	200NA	500MWF	6MA	12V	15V	1V			8MA	70dB	65dB	500K	
SF.C2458C	THF	DGK	INT		0.3V/uS	+18V	-18V	70C	88dB	6MV	500NA	200NA	680MWF	5MA	12V	15V	30V			6MA	70dB	77dB	300K	
SF.C2458DC	THF	DGK	INT			+18V	-18V	70C	86dB	6MV	500NA	200NA	500MWF	5MA	12V	15V	30V			6MA	70dB	77dB	300K	
SF.C2458M	THF	DGK	INT		.5MHZ	+22V	-22V	125C	94dB	5MV	500NA	200NA	680MWF	5MA	12V	15V	30V		150MW	5MA	70dB	76dB	300K	
SF.C2709A	THF	GPU	EXT	.3MHZ	15V/uS	+18V	-18V	125C	88dB	2MV	200NA	50NA	300MWF	7MA	12V	10V	5V	10uV/C	108MW	4MA	80dB	80dB	350K	
SF.C2709AE	THF	GPU	EXT	.3MHZ	15V/uS	+18V	-18V	70C	88dB	3.5MV	500NA	200NA	300MWF	5MA	12V	10V	5V	10uV/C	200MW	6MA	70dB	76dB	120K	
SF.C2709AP	THF	GPU	EXT	.3MHZ	15V/uS	+18V	-18V	125C	88dB	2MV	200NA	50NA	250MWF	7MA	12V	10V	5V	10uV/C	108MW	4MA	80dB	80dB	350K	
SF.C2709C	THF	GPU	EXT	.3MHZ	15V/uS	+18V	-18V	70C	84dB	7.5MV	1.5uA	500NA	300MWF	5MA	12V	10V	5V			200MW	7MA	65dB	74dB	50K
SF.C2709DC	THF	GPU	EXT	.3MHZ	15V/uS	+18V	-18V	70C	84dB	7.5MV	1.5uA	500NA	300MWF	5MA	12V	10V	5V			200MW	7MA	65dB	74dB	50K
SF.C2709EC	THF	GPU	EXT	.3MHZ	15V/uS	+18V	-18V	70C	84dB	7.5MV	1.5uA	500NA	300MWF	5MA	12V	10V	5V			200MW	7MA	65dB	74dB	50K
SF.C2709ET	THF	GPU	EXT		15V/uS	+18V	-18V	85C	88dB	5MV	750NA	300NA	300MWF	5MA	12V	10V	5V	20uV/C		7MA	65dB	74dB	70K	
SF.C2709KM	THF	GPU	EXT	.3MHZ	15V/uS	+18V	-18V	125C	88dB	5MV	500NA	200NA	300MWF	5MA	12V	10V	5V	15uV/C	165MW	6MA	70dB	76dB	150K	
SF.C2709M	THF	GPU	EXT	.3MHZ	15V/uS	+18V	-18V	125C	88dB	5MV	500NA	200NA	300MWF	5MA	12V	10V	5V	15uV/C	165MW	6MA	70dB	76dB	1	

For detailed explanations of column heading notations, see App. A.

Also for ready references the more important abbreviations used in the column headings are listed below:

LEFT HAND PAGE

APP = application

(codes at APP.E.)

CMRR = common mode

rejection ratio

CMP = compensation

(frequency)

$V_{IO}/\theta T$  = input offset voltage

temperature drift

GBP = gain bandwidth

product

$I_B$  = input bias current

$I_{in}$  = input bias offset

current

$I_Q$  = quiescent supply

current

MFR = manufacturer

(codes at App.C.)

$P_Q$  = quiescent power

consumer

PSRR = power supply rejection

ratio

$V_{ICM}$  = common mode input

voltage rating

$V_{IOF}$  = differential input

voltage rating

$V_{IO}$  = input offset voltage

$V_S$  = dc supply voltage

RIGHT HAND PAGE

Lead out coding summary

(details at APP.G.) for different cases (APP.F.)

A = gain adjust

B = bias adjust

C = case

E- = inverting input

E+ = non-inverting input

F,F\* = input frequency

compensation

G = ground

J = high level input

K = output, open collector

L = output, open emitter

M = metal case

N = not connected

Q = special terminal

R,R\* = outputs

S = strobe

T,T\* = offset balance

V+ = +ve dc supply

V- = -ve dc supply

W = guard ring

X = blank position, no lead

++ = +ve supplementary dc

supply

-- = -ve supplementary dc

supply

$\phi, \phi^*$  = output frequency

compensation

CASE (APP.F.)	LD 1	LD 2	LD 3	LD 4	LD 5	LD 6	LD 7	LD 8	LD 9	LD 10	LD 11	LD 12	LD 13	LD 14	LD 15	LD 16	EUROPE SUBSTITUTION	USA SUBSTITUTION	ISS	TYPE NUMBER
T05-8/1M	R1	E-1	E+1	V-	E+2	E-2	R2	V+	.	.	.	.	.	.	.	.	.	.	0	SE532T
DIL-8/1P	T	E-	E+	V-	T*	R	V+	N	.	.	.	.	.	.	.	.	.	SE535V	0	SE535N(8)
T05-8/1M	T	E-	E+	V-	T*	R	V+	N	.	.	.	.	.	.	.	.	.	.	0	SE535T
DIL-8/1P	T	E-	E+	V-	T*	R	V+	N	.	.	.	.	.	.	.	.	.	.	0	SE535V
T05-10/1M	B	E+	N	E-	B*	V-	L	Q	K	V+	.	.	.	.	.	.	.	.	0	SE540L
DIL-14/1P	E+	N	A2	A*2	V-	N	R	R*	N	V+	A1	A*1	N	E-	.	.	SN52733J	UA733DM	0	SE592A
DIL-14/1C	E+	N	A2	A*2	V-	N	R	R*	N	V+	A1	A*1	N	E-	.	.	SN52733J	UA733DM	0	SE592F
T05-10/1M	E-	E+	A2	A*2	V-	R	R*	V+	A1	A*1	.	.	.	.	.	.	SN52733L	UA733HM	0	SE592K
DIL-14/1P	E+	N	A2	A*2	V-	N	R	R*	N	V+	A1	A*1	N	E-	.	.	SN52733J	UA733DM	0	SE592N(14)
T05-8/1M	FT	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	UA2101A	LM101AH	0	SF.C2101A
FLP-10/3G	N	FT	E-	E+	V-	T*	R	V+	F*	N	.	.	.	.	.	.	UA101AF	LM101AF	0	SF.C2101APM
T05-8/1M	N	E-	E+	V-M	N	R	V+	N	.	.	.	.	.	.	.	.	UA107H	LM107H	0	SF.C2107
FLP-10/3G	N	N	E-	E+	V-	N	R	V+	N	N	.	.	.	.	.	.	.	LM107F	0	SF.C2107PM
T05-8/1M	F	E-	E+	V-M	N	R	V+	F*	.	.	.	.	.	.	.	.	UA108AH	LM108AH	0	SF.C2108A
T05-8/1M	F	E-	E+	V-M	N	R	V+	F*	.	.	.	.	.	.	.	.	UA108H	LM108	0	SF.C2108M
FLP-10/3G	N	N	E-	E+	N	V-	R	V+	F*	F	.	.	.	.	.	.	UA108F	LM108F	0	SF.C2108PM
T05-8/1M	T	N	E+	V-	L	R	V+	T*	.	.	.	.	.	.	.	.	UA110M	LM110M	0	SF.C2110M
T05-8/1M	G	E+	E-	V-	T	T*S	R	V+	.	.	.	.	.	.	.	.	SG111T	LM111H	0	SF.C2111M
T05-8/1M	T*F	E-	E+	V-	F*T	R	V+	$\phi$	.	.	.	.	.	.	.	.	TDC0118CM	LM118H	0	SF.C2118M
T05-8/1M	FT	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	UA201AH	LM201AH	0	SF.C2201A
FLP-10/3G	N	FT	E-	E+	V-	T*	R	V+	F*	N	.	.	.	.	.	.	UA201AF	LM201AF	0	SF.C2201APT
T05-8/1M	N	E-	E+	V-M	N	R	V+	N	.	.	.	.	.	.	.	.	UA207H	LM207H	0	SF.C2207
FLP-10/3G	N	N	E-	E+	V-	N	R	V+	N	N	.	.	.	.	.	.	LM207F	0	SF.C2207PT	
T05-8/1M	F	E-	E+	V-M	N	R	V+	F*	.	.	.	.	.	.	.	.	UA208H	LM208H	0	SF.C2208
T05-8/1M	F	E-	E+	V-M	N	R	V+	F*	.	.	.	.	.	.	.	.	UA208AH	LM208AH	0	SF.C2208A
FLP-10/3G	N	N	E-	E+	N	V-	R	V+	F*	F	.	.	.	.	.	.	UA208F	LM208F	0	SF.C2208PT
T05-8/1M	T	N	E+	V-	L	R	V+	T*	.	.	.	.	.	.	.	.	UA110M	LM210H	0	SF.C2210
T05-8/1M	G	E+	E-	V-	T	T*S	R	V+	.	.	.	.	.	.	.	.	SG211T	LM211H	0	SF.C2211
T05-8/1M	T*F	E-	E+	V-	F*T	R	V+	$\phi$	.	.	.	.	.	.	.	.	TDB0118CM	LM218H	0	SF.C2218
T05-8/1M	FT	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	UA301AH	LM301AH	0	SFC2301A
DIL-8/1G	FT	E-	E+	V-	T*	R	V+	F*	.	.	.	.	.	.	.	.	UA301AT	LM301AJ	0	SF.C2301ADC
T05-8/1M	N	E-	E+	V-M	N	R	V+	N	.	.	.	.	.	.	.	.	UA307H	LM307H	0	SF.C2307
DIL-8/1P	N	E-	E+	V-	N	R	V+	N	.	.	.	.	.	.	.	.	UA307T	LM307J	0	SF.C2307DC
T05-8/1M	F	E-	E+	V-M	N	R	V+	F*	.	.	.	.	.	.	.	.	UA308H	LM308H	0	SF.C2308
T05-8/1M	F	E-	E+	V-M	N	R	V+	F*	.	.	.	.	.	.	.	.	UA308AH	LM308AH	0	SF.C2308A
DIL-8/1P	F	E-	E+	V-	N	R	V+	F*	.	.	.	.	.	.	.	.	SN72308JP	LM308N	0	SF.C2308DC
T05-8/1M	T	N	E+	V-	L	R	V+	T*	.	.	.	.	.	.	.	.	UA310C	LM310H	0	SFC2310
DIL-8/1P	T	N	E+	V-	L	R	V+	T*	.	.	.	.	.	.	.	.	SN72310JP	LM310N	0	SF.C2310DC
DIL-14/1P	N	N	T	N	E+	V-	N	N	L	R	V+	T*	N	N	.	.	SN72310JA	LM310D	0	SF.C2310EC
T05-8/1M	G	E+	E-	V-	T	T*S	R	V+	.	.	.	.	.	.	.	.	UA311H	LM311H	0	SF.C2311
DIL-8/1P	G	E+	E-	V-	T	T*S	R	V+	.	.	.	.	.	.	.	.	UA311R	LM311N	0	SF.C2311DC
DIL-14/1P	N	G	E+	E-	N	V-	T	T*S	R	N	V+	N	N	N	.	.	SN72311J	LM311D	0	SF.C2311EC
DIL-6/1P	V+	E+	E-	V-	K	K*	.	.	.	.	.	.	.	.	.	.	TCA315A	0	SF.C2315DC	
T05-8/1M	T*F	E-	E+	V-	F*T	R	V+	$\phi$	.	.	.	.	.	.	.	.	TDE0118CM	LM318H	0	SF.C2318
DIL-14/1P	N	N	T*F	E-	E+	V-	N	N	F*T	R	V+	$\phi$	N	N	.	.	SN72318JA	LM318D	0	SF.C2318EC
T05-8/1M	R1	E-1	E+1	V-	E+2	E-2	R2	V+	.	.	.	.	.	.	.	.	TBB1458	MC1458G	0	SF.C2458C
DIL-8/1P	R1	E-1	E+1	V-	E+2	E-2	R2	V+	.	.	.	.	.	.	.	.	TBB1458B	MC1458J	0	SF.C2458DC
T05-8/1M	R1	E-1	E+1	V-	E+2	E-2	R2	V+	.	.	.	.	.	.	.	.	TBC1458	MC1558G	0	SF.C2458M
T05-8/1M	F	E-	E+	V-	$\phi$	$\phi^*R$	V+	F*	.	.	.	.	.	.	.	.	MC1709AG	UA709AHM	0	SF.C2709A
DIL-14/1P	N	N	F	E-	E+	V-	N	N	$\phi$	R	V+	F*	N	N	.	.	LM709AJ	UA709ADM	0	SF.C2709AE
FLP-10/3G	N	F	E-	E+	V-	$\phi$	R	V+	F*	N	.	.	.	.	.	.	.	UA709AFM	0	SF.C2709AP
T05-8/1M	F	E-	E+	V-	$\phi$	$\phi^*R$	V+	F*	.	.	.	.	.	.	.	.	TAA521	UA709HC	0	SF.C2709C
DIL-8/1P	F	E-	E+	V-	$\phi$	$\phi^*R$	V+	F*	.	.	.	.	.	.	.	.	LM709CN8	UA709TC	0	SF.C2709DC
DIL-14/1P	N	N	F	E-	E+	V-	N	N	$\phi$	R	V+	F*	N	N	.	.	LM709AJ	UA709ADM	0	SF.C2709EC
DIL-14/1C	N	N	F	E-	E+	V-	N	N	$\phi$	R	V+	F*	N	N	.	.	LM709AJ	UA709ADM	0	SF.C2709ET
DIL-14/1C	N	N	F	E-	E+	V-	N	N	$\phi$	R	V+	F*	N	N	.	.	LM709J	UA709DM	0	SF.C2709KM
T05-8/1M	F	E-	E+	V-	$\phi$	$\phi^*R$	V+	F*	.	.	.	.	.	.	.	.	TAA522	UA709HM	0	SF.C2709M
FLP-10/3G	N	F	E-	E+	V-	$\phi$	R	V+	F*	N	.	.	.	.	.	.	.	UA709FM	0	SF.C2709PM
FLP-10/3G	N	F	E-	E+	V-	$\phi$	R	V+	F*	N	.	.	.	.	.	.	.	UA709FM	0	SF.C2709PT
T05-8/1M	F	E-	E+	V-	$\phi$	$\phi^*R$	V+	F*	.	.	.	.	.	.	.	.	TAA522	UA709HM	0	SF.C2709T

# Appendix A

# Explanatory notes to tabulations

The general layout plan of the information in the tables of this compendium should be immediately evident from the data tabulation explanatory chart set out overleaf.

Supporting Appendices with additional information are:

- App. B Glossary of *Opamp Terms*
- App. C Tabulation *Codes for Manufacturers*
- App. D IC Manufacturers' *House Numbers*
- App. E Tabulation *Codes for Applications*
- App. F *Case Outline and Leadout Diagrams*
- App. G Codes for *Leadout Connections*

Unit symbols used in the tables are:

- A = amperes
- C = °centigrade
- dB = decibels
- G = gigaohms (megohms  $\times 10^3$ )
- GHZ = gigahertz (megahertz  $\times 10^3$ )
- K = kilohms
- KHZ = kilohertz
- M = megohms
- MA = milliamperes, mA
- MAX = maximum
- MHZ = megahertz
- MIN = minimum
- MV = millivolts
- MWC = milliwatts, case at 25C
- MWF = milliwatts, free air at 25C
- MWH = milliwatts, heat sink, 25C
- NA = nanoamps (microamps  $\times 10^{-3}$ )
- NV = nanovolts (microvolts  $\times 10^{-3}$ )
- PA = picoamps (microamps  $\times 10^{-12}$ )
- R = ohms
- T = teraohms (megohms  $\times 10^6$ )
- V = volts
- WC = watts, case at 25C
- WF = watts, free air at 25C
- WH = watts, heatsink, 25C
- $\mu$ A = microamps
- $\mu$ S = microseconds
- $\mu$ V = microvolts
- $\mu$ W = microwatts
- $\mu$ WF = microwatts, free air at 25C

Where a unit symbol appears in the middle of a value, it indicates the position of the decimal point, e.g. 3K3 = 3.3K.



## Appendix A

### LEFT HAND PAGE

For detailed explanations of column heading notations, see App. A.

Also for ready references the more important abbreviations used in the column headings are listed below:

- APP = application  
(codes at APP.E.)
- CMRR = common mode rejection ratio
- CMP = compensation  
(frequency)
- $dV_{io}/dT$  = input offset voltage temperature drift
- GBP = gain bandwidth product
- $I_B$  = input bias current
- $I_{IO}$  = input bias offset current
- $I_Q$  = quiescent supply current
- MFR = manufacturer  
(codes at App.C.)
- $P_Q$  = quiescent power consumer
- PSRR = power supply rejection ratio
- $V_{icm}$  = common mode input voltage rating
- $V_{idc}$  = differential input voltage rating
- $V_{io}$  = input offset voltage
- $V_S$  = dc supply voltage

### RIGHT HAND PAGE

Lead out coding summary (details at APP.G.) for different cases (APP.F.)

- A = gain adjust
- B = bias adjust
- C = case
- E- = inverting input
- E+ = non-inverting input
- F,F\* = input frequency compensation
- G = ground
- J = high level input
- K = output, open collector
- L = output, open emitter
- M = metal case
- N = not connected
- Q = special terminal
- R,R\* = outputs
- S = strobe
- T,T\* = offset balance
- V+ = +ve dc supply
- V- = -ve dc supply
- W = guard ring
- X = blank position, no lead
- + + = +ve supplementary dc supply
- - = -ve supplementary dc supply
- $\phi, \phi^*$  = output frequency compensation

CASE (APP. F.)	LD 1	LD 2	LD 3	LD 4	LD 5	LD 6	LD 7	LD 8	LD 9	LD 10	LD 11	LD 12	LD 13	LD 14	LD 15	LD 16	EUROPE SUBSTITUTION	USA SUBSTITUTION	ISS	TYPE NUMBER	
T05-8/1M	T	E-	E+	V-	T*	R	V+	N	.	.	.	.	.	.	.	.	.	.	LH0022H	0	LH0022CH

CASE = PACKAGE OF DIFFERENT TYPES CODED ACCORDING TO APP. F - FIRST NUMBER INDICATES NUMBER OF LEAD POSITIONS EG DIL-14 = 14 LEAD DUAL-IN-LINE PACKAGE

LD1, LD2, ETC = LEAD NUMBERS WITH CONNECTIONS ACCORDING TO PAGE FOOTNOTE OR APP. G.

EURO SUBSTITUTION = PROELECTRON STANDARD OR OTHER TYPE AVAILABLE IN EUROPE

USA SUBSTITUTION = SUGGESTED ALTERNATIVE AVAILABLE IN USA.

ISS = ISSUE NUMBER OF DATA ENTRY

TYPE No. REPEATED ON R.H. MARGIN

# Appendix C

## Tabulation Codes for Manufacturers

<b>ADU</b>	<b>Advanced Micro Devices Inc.,</b> 901 Thompson Pl., Sunnyvale, CA 94086, USA	<b>ITU</b>	DA14 5HT, UK <b>ITT Semiconductors</b> 74 Commerce Way, Woburn, MA, 01801, USA
<b>ANG</b>	<b>Analog Devices Ltd,</b> Central Ave., East Molesey, KT8 9BR, Surrey, UK	<b>MNG</b>	<b>Mitsubishi Shoji Kaisha Ltd,</b> Bow Bells House, Bread St., London, EC4, UK
<b>ANU</b>	<b>Analog Devices Inc.,</b> P.O. Box 280, Norwood, Mass., 02062	<b>MNJ</b>	<b>Mitsubishi Electric Corp.,</b> 2-12 Marunouchi, Chiyoda-ku, Tokyo, Japan
<b>BLG</b>	<b>Bell &amp; Howell Ltd,</b> Lennox Road, Basingstoke, Hants, UK	<b>MTG</b>	<b>Motorola Ltd</b> (Semiconductor Products Div.), York House, Empire Way, Wembley, Middlesex, HA9 0PR, UK
<b>BLU</b>	<b>Bell &amp; Howell</b> (Control Products Divison), 706 Bostwick Ave, Bridgeport, Conn. 06605, USA	<b>MTU</b>	<b>Motorola Semiconductor Products Inc.,</b> 5005 E. McDowell Road, Phoenix, AZ, 85008, USA
<b>BUG</b>	<b>Burr-Brown International Ltd,</b> 17 Exchange Rd, Watford, WQD1 7EB, Herts., UK	<b>MUG</b>	<b>Mullard Ltd,</b> Mullard House, Torrington Place, London, WC1E 7HD, UK
<b>BUU</b>	<b>Burr-Brown Research Corp.,</b> P.O. Box 11400, Tucson, AZ, 85734, USA	<b>NAG</b>	<b>National Semiconductor (UK) Ltd,</b> Harpur Centre, Bedford, MK40 3LF, UK
<b>CMG</b>	<b>Computing Techniques Ltd,</b> Brookers Rd, Billingshurst, Sussex, RH14 9RZ, UK	<b>NAU</b>	<b>National Semiconductor Corp.,</b> 2900 Semiconductor Drive, Santa Clara, CA, 95051, USA
<b>DAG</b>	<b>Datel UK Ltd,</b> Stephenson Close, Portway Ind. Estate, Andover, Hants, UK	<b>NIJ</b>	<b>Nippon Electric Co. Ltd,</b> 1753 Shimonumabe, Nakahara-ku, Kawasaki, Japan
<b>DAU</b>	<b>Datel Systems Inc.,</b> 1020 Turnpike St., Canton, MA 02021, USA	<b>OAU</b>	<b>Opamp Labs Inc.,</b> 1033 N. Sycamore Ave., Los Angeles, CA 90038, USA
<b>FAG</b>	<b>Fairchild Camera &amp; Instrument (UK) Ltd,</b> 230 High St., Potters Bar, Herts., UK	<b>OBS</b>	Obsolete – no longer commercially available.
<b>FAU</b>	<b>Fairchild Semiconductor</b> 464 Ellis St., Mountain View, CA 94042, USA	<b>OTU</b>	<b>Optical Electronics Inc.,</b> P.O. Box 11140, Tucson, AZ, 85734, USA
<b>FEG</b>	<b>Ferranti Ltd,</b> (Electronic Department), Gem Mill, Chadderton, Oldham, Lancs., OL9 8NP, UK	<b>PLG</b>	<b>Plessey Semiconductors,</b> Cheney Manor, Swindon, Wilts., SN2 2QW, UK
<b>FUJ</b>	<b>Fujitsu Ltd,</b> 1015 Kamikodanaka, Kawasaki, Japan	<b>PRG</b>	<b>Precision Monolithics</b> (Bourns Trimpot Ltd) 17/27 High St., Hounslow, Middlesex, UK
<b>HAG</b>	<b>Harris Semiconductor (Memec) Ltd,</b> The Firs, Whitchurch, Nr. Aylesbury, Bucks., HP22 4JU, UK	<b>PRU</b>	<b>Precision Monolithics (Bourns) Inc.,</b> 1500 Space Park Drive, Santa Clara, CA, 95050, USA
<b>HAU</b>	<b>Harris Semiconductor</b> P.O. Box 883, Melbourne, FL, 32901, USA	<b>RAG</b>	<b>Raytheon Semiconductor</b> The Pinnacles, Harlow, Essex, CM19 5BB, UK
<b>HIJ</b>	<b>Hitachi Ltd</b> (Semiconductor and IC Div.), 1450 Josuihonimachi, Kodaira City, Tokyo, Japan	<b>RAU</b>	<b>Raytheon Semiconductor,</b> 350 Ellis Street, Mountain View, CA, 94042, USA
<b>ING</b>	<b>Intersil Inc.,</b> 8 Tessa Rd, Richfield Trading Estate, Reading, Berks., UK	<b>RCG</b>	<b>RCA (Great Britain) Ltd,</b> Lincoln Way, Windmill Road, Sunbury-on- Thames, Middlesex, UK
<b>INU</b>	<b>Intersil Inc.,</b> 10900 N. Tantau Ave, Cupertino, CA, 95014, USA	<b>RCU</b>	<b>RCA Solid State Division</b> Route 202, Somerville, NJ, 08876, USA
<b>ITG</b>	<b>ITT Semiconductors</b> Maidstone Rd, Fooks Cray, Sidcup, Kent,	<b>SAJ</b>	<b>Sanken Electric Co. Ltd,</b> 1-22-8 Nishi-Ikebukuro, Toshima-Ku, Tokyo, Japan

Appendix C

<b>SGG</b>	<b>SGS-ATES (UK) Ltd,</b> Planar House, Walton Street, Aylesbury, Bucks., UK	<b>SPU</b>	<b>Sprague Electric Company</b> (Semiconductor Div.), 115 Northeast Cutoff, Worcester, MA, 01606, USA
<b>SGI</b>	<b>SGS-ATES Componenti Spa,</b> Via Olivetti, 2 Agrate Brianza, 20041, Milan, Italy	<b>TDG</b>	<b>Teledyne Semiconductor,</b> Heathrow House, Bath Road, Cranford, Hounslow, Middlesex, TW5 9QP, UK
<b>SHG</b>	<b>Shindengen Hyokuto Boeki Haisha Ltd,</b> St. Alphage House, Fore St., London, EC2Y 5DA, UK	<b>TDU</b>	<b>Teledyne (Amelco) Semiconductor,</b> 1300 Terra Bella Ave, Mountain View, CA, 94032, USA
<b>SHJ</b>	<b>Shindengen Electric Mfg Co., Ltd,</b> New Ohtemachi Bldng, 2-1, 2-chome, Ohtemachi, Chiyoda-ku, Tokyo, Japan	<b>TEB</b>	<b>Teledyne-Philbrick,</b> Heathrow House, Bath Road, Cranford, Hounslow, Middlesex, TW5 9QP, UK
<b>SIG</b>	<b>Siemens Ltd,</b> Great West Road, Brentford, Middlesex, TW8 9DG, UK	<b>TEU</b>	<b>Teledyne-Philbrick,</b> Allied Drive at Route 128, Dedham, MA, 02026, USA
<b>SIW</b>	<b>Siemens Aktiengesellschaft,</b> Richard-Strauss-Strasse 76, D-8000 Munchen 2, Postfach 202109, W. Germany	<b>TGG</b>	<b>Texas Instruments Ltd,</b> Manton Lane, Bedford, UK
<b>SJG</b>	<b>Signetics International Corporation</b> Yeoman House, 63 Croydon Rd, London, SE20, UK	<b>TGU</b>	<b>Texas Instruments Inc.</b> (Components Group), P.O. Box 5012, Dallas, Texas, 75222, USA
<b>SJU</b>	<b>Signetics Corp.,</b> 811 East Arques Ave, Sunnydale, CA. 94086, USA	<b>THF</b>	<b>Thomson-CSF (Sescosem),</b> 50 Rue Jean Pierre Timbaud, BP 120, 92403, Courbevoie, France
<b>SKU</b>	<b>Silicon General Inc.,</b> 7382 Bolsa Avenue, Westminster, CA, 92683, USA	<b>THG</b>	<b>Thomson-CSF (UK) Ltd,</b> Ringway House, Bell Rd, Daneshill, Basingstoke, Hants., RG24 0QG, UK.
<b>SLG</b>	<b>Siliconix Ltd,</b> 30A High St., Thatcham, Newbury, Berks., RG13 4JG, UK	<b>TKJ</b>	<b>Tokyo Sanyo Electric Co. Ltd</b> (Semiconductor Div.), Oizumachi, Oragun, Gumma, Japan
<b>SLU</b>	<b>Siliconix Incorporated,</b> 2201 Laurelwood Road, Santa Clara, CA, 95054, USA	<b>TOG</b>	<b>Toshiba (UK) Ltd,</b> Toshiba House, Great South West Rd, Feltham, Middlesex, UK
<b>SOJ</b>	<b>Sony Semiconductor Corp.,</b> 14-1, Asa hi-sho 4, Atsuigi-shi, Kanagawa-ken, 243, Japan	<b>TOJ</b>	<b>Toshiba (Tokyo Shibaura) Electric Co.,</b> 2-1, 5-chome, Ginza Chuo-ku, Tokyo, Japan
<b>SPG</b>	<b>Sprague Electric (UK) Ltd,</b> 159 High St., Yiewsley, W. Drayton, Middlesex, UB7 7RY, UK	<b>TRU</b>	<b>Transitron Electronic Corp.,</b> 168 Albion St., Wakefield, MA, 01881, USA
		<b>ZEU</b>	<b>Zeltex Inc.,</b> 940 Detroit Ave, Concord, CA, 94518, USA

# Appendix D

## IC Manufacturers'

### House Numbers

(General Note: Manufacturers often adopt their own 'in-house' serial numbering for their ICs. Listed below are the initial letters of numerical series used by different manufacturers.)

<b>AD</b>	Analog Devices	<b>OP</b>	Precision Monolithics
<b>ADO</b>	Analog Devices	<b>P</b>	Teledyne-Philbrick
<b>AM</b>	Advanced Micro Devices; Datel	<b>PF</b>	Teledyne-Philbrick
<b>AMD</b>	Advanced Micro Devices	<b>PG</b>	General Instruments (obs.)
<b>AMLM</b>	Advanced Micro Devices	<b>PP</b>	Teledyne-Philbrick
<b>AMSSS</b>	Advanced Micro Devices	<b>RA</b>	Radiation (now Harris)
<b>AMU</b>	Advanced Micro Devices	<b>RC</b>	Raytheon
<b>C</b>	Bell & Howell	<b>RL</b>	Raytheon
<b>CA</b>	RCA	<b>RM</b>	Raytheon
<b>CIA</b>	Teledyne-Philbrick	<b>RSN</b>	Raytheon
<b>CMP</b>	Precision Monolithics	<b>RV</b>	Raytheon
<b>CN</b>	Ferranti	<b>S</b>	Signetics
<b>DA</b>	Teledyne-Philbrick	<b>SA</b>	Teledyne-Philbrick
<b>EP</b>	Teledyne-Philbrick	<b>SE</b>	Signetics; Mullard
<b>ESL</b>	Teledyne-Philbrick	<b>SFC</b>	Thomson-CSF
<b>FSL</b>	Teledyne-Philbrick	<b>SG</b>	Silicon General
<b>FSS</b>	Ferranti	<b>SH</b>	Fairchild
<b>HA</b>	Harris	<b>SK</b>	RCA
<b>HEPC</b>	Motorola	<b>SL</b>	Plessey; Teledyne-Philbrick
<b>ICH</b>	Intersil	<b>SN</b>	Texas Instruments
<b>ICL</b>	Intersil	<b>SP</b>	Teledyne-Philbrick
<b>JM</b>	Fairchild	<b>SQ</b>	Teledyne-Philbrick
<b>JSF</b>	Thomson-CSF	<b>SSS</b>	Precision Monolithics
<b>L</b>	Analog Devices; SGS-ATES	<b>SU</b>	Signetics; Mullard
<b>LA</b>	Teledyne-Philbrick	<b>T</b>	Teledyne-Philbrick Transitron
<b>LF</b>	National Semiconductor	<b>TA</b>	AEG-Telefunken
<b>LH</b>	National Semiconductor	<b>TAA</b>	Proelectron Standard
<b>LM</b>	National Semiconductor	<b>TBA</b>	Proelectron Standard
<b>M</b>	Mitsubishi	<b>TBB</b>	Proelectron Standard
<b>MC</b>	Motorola Semiconductors	<b>TBC</b>	Proelectron Standard
<b>MCC</b>	Motorola Semiconductors	<b>TBE</b>	Proelectron Standard
<b>MCCF</b>	Motorola Semiconductors	<b>TCA</b>	Proelectron Standard
<b>MCE</b>	Motorola Semiconductors	<b>TDA</b>	Proelectron Standard
<b>MCH</b>	Motorola Semiconductors	<b>TDB</b>	Proelectron Standard
<b>MIC</b>	ITT Semiconductors	<b>TDC</b>	Proelectron Standard
<b>MLF</b>	Motorola; Teledyne-Philbrick	<b>TDE</b>	Proelectron Standard
<b>MLM</b>	Motorola Semiconductors	<b>TL</b>	AEG-Telefunken
<b>MLMC</b>	Motorola Semiconductors	<b>TOA</b>	Transitron
<b>MONO-OP</b>	Precision Monolithics	<b>TSC</b>	Transitron
<b>N</b>	Signetics; Mullard	<b>U</b>	Fairchild
<b>NC</b>	General Instruments (obs.)	<b>ULN</b>	Sprague
<b>NE</b>	Signetics; Mullard	<b>ULS</b>	Sprague
<b>NH</b>	National Semiconductor	<b>USL</b>	Teledyne-Philbrick
		<b>ZA</b>	Zeltex
		<b>ZEL</b>	Zeltex
		<b>ZLD</b>	Ferranti
		<b>ZN</b>	Ferranti
		<b>μA</b>	Fairchild



# Appendix E

## Tabulation Codes for Applications

<b>BDO</b>	Balanced differential-output amplifier	<b>PAA</b>	Parametric amplifier
<b>CDA</b>	Current-difference amplifier	<b>PIA</b>	Precision instrumentation amplifier
<b>CHP</b>	Chopper-stabilized amplifier	<b>PRA</b>	Programmable opamp
<b>CPR</b>	DC comparator	<b>QCD</b>	Quad current-difference amplifier
<b>DBD</b>	Dual balanced differential-output amplifier	<b>QCP</b>	Quad comparator
<b>DCP</b>	Dual Comparator	<b>QFE</b>	Quad fet-input opamp
<b>DFE</b>	Dual fet-input opamp	<b>Q GK</b>	Quad general-purpose, internally-compensated, opamp
<b>DGK</b>	Dual general purpose opamp	<b>QGU</b>	Quad general-purpose, uncompensated, opamp
<b>DGU</b>	Dual general-purpose uncompensated opamp	<b>QLQ</b>	Quad low-quiescent-power opamp
<b>DHS</b>	Dual high-slew-rate opamp	<b>QPI</b>	Quad precision instrumentation amplifier
<b>DLN</b>	Dual low-noise opamp	<b>QPR</b>	Quad programmable opamp
<b>DPI</b>	Dual precision instrumentation amplifier	<b>QSB</b>	Quad super-beta opamp
<b>DPR</b>	Dual programmable opamp	<b>SBA</b>	Super-beta opamp
<b>DSB</b>	Dual super-beta opamp	<b>TCP</b>	Triple comparator
<b>FET</b>	Fet-input opamp	<b>TFE</b>	Triple fet-input opamp
<b>GPK</b>	General-purpose, internally-compensated, opamp	<b>TGK</b>	Triple general-purpose, internally compensated, opamp
<b>GPU</b>	General-purpose, uncompensated, opamp	<b>TGU</b>	Triple general-purpose, uncompensated, opamp
<b>HCO</b>	High current output opamp	<b>TLN</b>	Triple low-noise opamp
<b>HIR</b>	High input resistance opamp	<b>TLP</b>	Triple low-quiescent-power opamp
<b>HPO</b>	High power output opamp	<b>TOT</b>	Triple operational transconductance amplifier
<b>HSR</b>	High slew rate opamp	<b>TPI</b>	Triple precision instrumentation amplifier
<b>HVO</b>	High voltage output opamp	<b>TPR</b>	Triple programmable opamp
<b>LBC</b>	Low input bias current opamp	<b>TSB</b>	Triple super-beta opamp
<b>LCD</b>	Low input offset current drift opamp	<b>VFA</b>	Voltage-follower amplifier
<b>LNA</b>	Low noise opamp	<b>WBA</b>	Wide-band opamp
<b>LOC</b>	Low input offset current opamp	<b>XHG</b>	Extra-high-gain opamp
<b>LOV</b>	Low input offset voltage opamp	<b>XLP</b>	Extra-low quiescent power opamp
<b>LQP</b>	Low quiescent power opamp	<b>XSR</b>	Extra-high slew rate opamp
<b>LVD</b>	Low input offset voltage drift opamp	<b>XWB</b>	Extra-wide-band opamp
<b>MWB</b>	Medium-wideband opamp		
<b>OTA</b>	Operational transconductance amplifier		

# Appendix G

## Codes for Leadout Connections

### *I: Connection Codes in Serial Order*

A	= Gain adjust, 1
A*	= Gain adjust, 2
B	= Bias adjust or set
C	= Case, package, screen
E+	= Input, non-inverting, low-level
E-	= Input, inverting, low-level
F	= Input frequency compensation, 1
F*	= Input frequency compensation, 2
G	= Ground, common, earth, zero volts
J+	= Input, non-inverting, high-level
J-	= Input, inverting, high-level
K	= Output, open collector
L	= Output, open emitter
M	= Metal casing
N	= Not connected, i.e. isolated lead
Q	= Special terminal (consult manufacturer's data)
R	= Output, 1
R*	= Output, 2
S	= Strobe
T	= Offset balance, trim or null, 1
T*	= Offset balance, trim or null, 2
V+	= +ve dc supply
V-	= -ve dc supply
W	= Guard ring
X	= Blank position, lead omitted
++	= +ve supplementary dc supply
--	= -ve supplementary dc supply
φ	= Output frequency compensation, 1
φ*	= Output frequency compensation, 2

### *II: Lead Assignments in Alphabetical Order*

Balance, offset, 1 = T
Balance, offset, 2 = T*
Bias adjust = B
Blank position, without lead = X
Case = C
Compensation, input, 1 = F
Compensation, input, 2 = F*
Compensation, output, 1 = φ
Compensation, output, 2 = φ*
DC supply, +ve = V+
DC supply, -ve = V-
Frequency compensation, input, 1 = F
Frequency compensation, input, 2 = F*
Frequency compensation, output, 1 = φ
Frequency compensation, output, 2 = φ*
Gain adjust, 1 = A
Gain adjust, 2 = A*
Ground = G
Guard ring = W
Input, inverting, high-level = J-
Input, non-inverting, high-level = J+
Input, inverting, low-level = E-
Input, non-inverting, low-level = E+
Input offset voltage, adjust, 1 = T
Input offset voltage, adjust, 2 = T*
Lead omitted, blank position = X
Lead in position but not connected = N
Metal case = M
Not connected, but lead in position = N
Null, offset, 1 = T
Null, offset, 2 = T*
Offset voltage adjust, 1 = T
Offset voltage adjust, 2 = T*
Output, 1 = R
Output, 2 = R*
Output, open-collector = K
Output, open-emitter = L
Package = C
Special purpose terminal (data sheet to be consulted) = Q
Strobe = S
Supply, dc, +ve = V+
Supply, dc, -ve = V-
Supply, dc, supplementary, +ve = ++
Supply, dc, supplementary, -ve = --
Trim (offset voltage), 1 = T
Trim (offset voltage), 2 = T*

Appendix F



Appendix F

